


# Datasheet Series PLI

<b>Model</b>	<b>PLI6006ZV</b>	
<b>Order no.</b>	<b>17-031-002-02</b>	
<b>Basic operating modes</b>	CC, CV, CR, CP	
<b>Standard interfaces</b>	RS-232, USB, LAN, CAN	
<b>Max. input voltage Vmax</b>	60 V	
<b>Min. input voltage Vmin <sup>1)</sup></b>	0.01 V	
<b>Max. load current Imax</b>	720 A	
<b>Continuous power</b>	6000 W	
<b>Short-time power <sup>2)</sup></b>	14000 W	
<b>Voltage setting</b>	0 ... 60 V	
<b>Current ranges</b>	0 ... 720 A	
<b>Resistance ranges</b>	0.00277 Ohm ... 0.8961 Ohm	
<b>Power ranges continuous/short-time <sup>3)</sup></b>	0 ... 14000 W	
<b>Rise and fall time fast / medium / slow <sup>4)</sup></b>	30 µs	
<b>Input capacity</b>	12 µF	
<b>Load terminals (front) <sup>5)</sup></b>	-	
<b>Load terminals (rear) <sup>6)</sup></b>	FKS25/10-SM10	
<b>Mains voltage <sup>7)</sup></b>	3/N/PE AC 400/230 V 50 ... 60 Hz	
<b>Mains voltage toggleable <sup>8)</sup></b>	-	
<b>Power consumption</b>	3300 VA	
<b>Max. noise <sup>9)</sup></b>	80 dB(A)	
<b>Weight ca.</b>	76.5 kg	
<b>Housing / 3D model <sup>10)</sup></b>	19" - 11 U / PLI_M27	

1. Minimum input voltage for maximum static load current.
2. Level and duration of the peak power depend on the previous power.
3. The setting range extends max. to the possible peak power.
4. Rise and fall times are defined of 10 % ... 90 % and 90 % ... 10 % of the maximum current (CC mode, fast regulation speed, tolerance ±20 %). Rise and fall time at setting "medium": ca. 150 µs, "slow": ca. 2 ms.
5. BPK4-30L: Touch-protected binding posts for 4 mm laboratory jacks and stripped wires with diameter up to 4 mm, max. 30 A  
BPK4-60L: Touch-protected binding posts for 4 mm laboratory jacks and stripped wires with diameter up to 6 mm, max. 60 A  
FKS20/5-SM8: Flat copper bars 20 x 5 mm vertical with hole for screw M8  
FKS25/8-SM10: Flat copper bars 25 x 8 mm vertical with hole for screw M10  
FKS25/10-SM10: Flat copper bars 25 x 10 mm vertical with hole for screw M10  
FKS40/12-SM12: Flat copper bars 40 x 12 mm vertical with hole for screw M12

# Datasheet Series PLI

6. BPK4-30L: Touch-protected binding posts for 4 mm laboratory jacks and stripped wires with diameter up to 4 mm, max. 30 A  
BPK4-60L: Touch-protected binding posts for 4 mm laboratory jacks and stripped wires with diameter up to 6 mm, max. 60 A  
FKS20/5-SM8: Flat copper bars 20 x 5 mm vertical with hole for screw M8  
FKS25/8-SM10: Flat copper bars 25 x 8 mm vertical with hole for screw M10  
FKS25/10-SM10: Flat copper bars 25 x 10 mm vertical with hole for screw M10  
FKS40/12-SM12: Flat copper bars 40 x 12 mm vertical with hole for screw M12
7. Mains voltage tolerance:  $\pm 10\%$
8. Mains voltage tolerance:  $\pm 10\%$
9. Measured on the front from distance of 1 m.
10. Largest width and depth without wiring. 1 U = 44.45 mm.

Operating modes		
Basic operating modes	CC, CV, CR, CP	
Combined operating modes	CC+CV, CR+CC+CV, CP+CC+CV, CV+CC	
Accuracy of setting		
	of setting	of corresponding range
Voltage	±0.2 %	±0.05 %
Current	±0.2 %	±0.05 %
Resistance (at 5 % to 100 % of voltage range)	±1.4 %	±0.3 % of current range
Power (at V and I > 30 % of range) (at V or I < 30 % of range)	±0.35 %	±0.1 %
	±0.7 %	±0.25 %
Resolution	14 bits	
Accuracy of adjustable protections		
	of setting	of corresponding range
Overcurrent protection	±1.4 %	±0.3 %
Undervoltage protection	±1.4 %	±0.3 %
Resolution	12 bits	
Accuracy of measurement slow		
	of measured value (real value)	of corresponding range
Voltage	±0.01 %	±0.005 %
Current	±0.2 %	±0.05 %
Resistance	is calculated from current and voltage	
Power	is calculated from current and voltage	
Resolution	23 bits	
Sampling rate	250 ms, not triggerable	
Accuracy of display		
Number of decimal places	5	
Accuracy	Accuracy of measurement slow ±1 digit of the display value	
Accuracy of measurement fast		
	of measured value (real value)	of corresponding range
Voltage	±0.1 %	±0.05 %
Current	±0.2 %	±0.1 %
Resistance	calculated from voltage and current values	
Power	calculated from voltage and current values	
Resolution	16 Bit	
Sampling rate	200 µs ... 1000 s	
Accuracy of trigger voltage and current measurement		
Voltage	±1 % of range	
Current	±1 % of range	
Dynamic function (LIST)		
No. of load levels	max. 300, with ramp and dwell time setting	
	min.	max.
Dwell time	200 µs	1000 s
Ramp time	0 s	1000 s
Resolution	200 µs	
Accuracy of the setting times	±0.02 %	
Delay at triggered start	max. 300 µs	

Data acquisition		
to external USB flash drive		
Sampling rate	0.5 to 30 s, resolution 0.1 s	
Measurement data	timestamp, voltage, current	
No. of measurement points	limited by USB memory capacity	
File format	.csv	
to internal memory		
Sampling rate	200 µs ... 1000 s, resolution 200 µs, synchronized with dynamic function	
Measurement data	timestamp, voltage, current	
No. of measurement points	max. 40,000	
Settings memories		
No. of user settings	9, selectable (incl. programmed list) 1 for last device settings at power-off or power fail	
I/O port: accuracy of analog control 0 ... 10 V		
	of setting	of corresponding range
Voltage	±0.2 %	±0.1 %
Current	±0.2 %	±0.1 %
Overcurrent protection	±1 %	±0.4 %
Undervoltage protection	±1 %	±0.4 %
	Input resistance of analog inputs >10 kΩ	
I/O port: accuracy of analog monitor outputs 0 ... 10 V		
	of analog signal of real value	offset voltage
Voltage	±0.2 %	±15 mV
Current	±0.2 %	±15 mV
	load capacity minimal 2 kΩ	
I/O port: permissible voltages		
	standard I/O port	isolated I/O port (option PLI06)
Vin-io (GND - neg. load input)	PLIxxxxZV: must be galvanically isolated all others: max. 2 V <sup>1)</sup>	PLIxxxxZV: max. 2 V <sup>1)</sup> all others: max. 800 V <sup>1)</sup>
VioPE (GND - PE)	max. 125 V <sup>1)</sup>	max. 125 V <sup>1)</sup>
I/O port: control outputs and inputs		
Outputs	activation state load input (low active) status overload (OV, OCP, OPP, OTP, low active) trigger output (low active) programmable logic output (by SCPI command)	
Output level	selectable, 3.3 V, 5 V, 12 V or externally programmable up to 30 V	
Control inputs	activation state load input (low active) operating mode selection trigger input (high active) readable logic input (by SCPI command) control input (activates the analog signals, low active) remote shut-down (low active)	
input level	3 ... 30 V	

The specified accuracies refer to an ambient temperature of 23 ±5 °C. The specified accuracies are valid when the unit is connected to undisturbed voltages (ripple and noise < 0.1 %). At voltages with higher disturbance values the accuracy can change for the worse.

<sup>1)</sup> positive/negative DC voltage or RMS value of a sinusoidal AC voltage

## Technical Data (continued)

Input		
Input resistance	> 50 kΩ when load input is off diode function at reverse polarity up to nominal current, except ZV models	
Input capacity	see model overview	
Parallel operation	up to 5 devices in Master-Slave operation	
Max. input voltage	see model overview	
Min. input voltage	see model overview	
Input: permissible voltages		
	<b>standard I/O port</b>	<b>isolated I/O port (option PLI06)</b>
Vin-PE (neg. load input - PE)	max. 125 V <sup>1)</sup>	PLIxxxxZV: max. 125 V <sup>1)</sup> all others: max. 800 V <sup>1)</sup>
Vin+PE (pos. load input - PE)	Vmax + max. 125 V <sup>1)</sup>	PLIxxxxZV: Vmax + max. 125 V <sup>1)</sup> all others: Vmax + max. 800 V <sup>1)</sup>
Power		
Continuous power	see model overview (at Ta = 21 °C)	
Derating	-1.2 %/°C for Ta > 21 °C	
Overload capability (short-time power)	see model overview The max. possible overload Po depends on the temperature of the device and therefore on the previously consumed continuous power Pd. The possible overload duration depends on the value of the overload Px.	
Protection and monitoring		
Protective devices	overcurrent overpower overtemperature	
Monitoring	overvoltage indication reverse polarity indication undervoltage indication (if the input voltage is too low for the set current)	
Terminals		
Load input	see model overview	
Sense	PH2/7.62-BU16, incl. mating connector from PHOENIX CONTACT (Phoenix order no.: 1745629)	
Operating conditions		
Operating temperature	5 ... 40 °C	
Stock temperature	-25 ... 65 °C	
Max. operating height	2,000 m above sea level	
Pollution degree	2	
Overvoltage category of mains	II	
Max. humidity	80 % at 31 °C, linear decreasing to 50 % at 40 °C	
Min. distance rear panel to wall or other objects	70 cm	
Cooling	3-stage air cooling, up from 3200 W variably controlled	
Noise, weight	see model overview	
Mains voltage	see model overview	
Power consumption	see model overview	

Housing	
Color	
Front	RAL7035 (light grey)
Rear	stainless steel
Top, side panels	RAL7037 (dusty grey)
Safety and EMC	
Protection class	1
Protection	IP20
Measuring category	0 (CAT I according to EN61010:2004)
Electrical safety	DIN EN 61010-1 DIN EN 61010-2-030
EMC	DIN EN 61326-1 DIN EN 55011 DIN EN 61000-3-2 DIN EN 61000-3-3
Standard interfaces	
Data interfaces	RS-232, USB, LAN, CAN
I/O port	standard I/O port (not isolated)
Available options	
Data interfaces PLI02	GPIB
Mechanical options PLI10 PLI11 PLI12 PLI13 PLI14	19" installation kit for 1 device with ½ 19"; 2 U 19" installation kit for 2 devices with ½ 19"; 2 U 19" installation kit for 1 device with 19"; 2 U 19" installation kit for 1 device with 19"; 3 U heavy-load castors (5 U and upwards)
Function enhancement PLI21	MPPT function with activation code see accuracy of measurement fast
Hardware extensions PLI06	galvanically isolated I/O port
PLI16-06 PLI16-12	Charger Starter Interface (CSI) for 60 V models (6 ... 60 V) Charger Starter Interface (CSI) for 120V models (6 ... 120V) ±1 % ±200 mV max. 0.1 A can be coupled with activation state of load input 0.1 ... 100 s ±0.3 s
PLI17	switch box for external load activation via I/O port
DC mains supply PLI18 PLI19	12 V DC mains supply (only for PLI14xx) 12 V DC mains supply (only for PLI32xx with housing extension to 5 U, toggling by mains selection switch)
Calibration, warranty	
FCC-PLIxx	Factory Calibration Certificate, twice for free
Warranty	2 years

<sup>1)</sup> positive/negative DC voltage or RMS value of a sinusoidal AC voltage